

ORIGINAL - FESTOON

Original spare part



The cost-effective original spare parts

The ORIGINAL festoon lamps with OSRAM's reliable OEM quality can be used as original spare parts for a wide range of festoon lamps. The typical application areas of the lamps are number plate and side position lights as well as interior lighting and reading lights.

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	6428
------------------------	------

Electrical Data

Power input	3.5 W
Nominal voltage	12 V
Nominal wattage	3 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometric Data

Nominal luminous flux	29 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions



Diameter	8 mm
Product weight	1.76 g
Length	28.0 mm
Lamp base	SV7-8

Lifetime Data

Lifespan B3	600 hr
Lifespan Tc	1200 hr

Product datasheet

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	-
--------------	---

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Primary article identifier	4008321007957 4008321094384
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	No declarable substances contained

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321094384	OSRA6428	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094384	ORIGINAL FESTOON 6428	Unpacked 1	28 mm x 8 mm x 8 mm	0.00 dm ³	2.00 g
4008321094407	ORIGINAL FESTOON 6428	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm ³	208.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

File	
	User instruction GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM